

Specification and Adjustment Manual - ARDAC IBA5  
Document Number 44X501 – Initial Release January, 2004

<b>SWITCH BANK 1</b>		<b>SWITCH OFF (Enable)</b>	<b>SWITCH ON (Inhibit)</b>
SWITCH 1-1	NOTE 1 (Lowest Value)	ACCEPT NOTE 1	INHIBIT NOTE 1
SWITCH 1-2	NOTE 2	ACCEPT NOTE 2	INHIBIT NOTE 2
SWITCH 1-3	NOTE 3	ACCEPT NOTE 3	INHIBIT NOTE 3
SWITCH 1-4	NOTE 4	ACCEPT NOTE 4	INHIBIT NOTE 4
SWITCH 1-5	NOTE 5	ACCEPT NOTE 5	INHIBIT NOTE 5
SWITCH 1-6	NOTE 6	ACCEPT NOTE 6	INHIBIT NOTE 6
SWITCH 1-7	NOTE 7	ACCEPT NOTE 7	INHIBIT NOTE 7
SWITCH 1-8	UNDEFINED	UNDEFINED	UNDEFINED

<b>SWITCH BANK 2</b>		<b>SWITCH OFF</b>	<b>SWITCH ON</b>
SWITCH 2-1	PROTOCOL*	NETPLEX	PULSED (IBA4 only)
SWITCH 2-2	BARCODE	ENABLE	DISABLE
SWITCH 2-3	MAG SENSOR	DISABLED	ENABLED
SWITCH 2-4	STRING SENSOR	ENABLE	DISABLE
SWITCH 2-5	SMART CASSETTE	DISABLE	ENABLE
SWITCH 2-6	FIRMWARE DEVICE	EPROM	FLASH

<b>SWITCH BANK 2-7 AND 2-8</b>	<b>FUNCTION</b>
SW2-7 = OFF, SW2-8 = OFF	NORMAL OPERATION
SW2-7 = OFF, SW2-8 = ON	CALIBRATION CARD MODE
SW2-7 = ON, SW2-8 = OFF	CLEANING CARD MODE
SW2-7 = ON, SW2-8 = ON	UNDEFINED

**\* IBA-5 Operates in Netplex protocol only.**

**Table 1-1**