

**TITO Setup Bally EVO Hybrid Slot**

**To set up TITO you must RAM CLEAR the slot and start initial game install.**

1. Make sure **ALL POWER is off** on your slot
2. Remove MPU board and locate IC socket U78. Insert EVO CLEAR chip in this socket and orient the notch on the IC socket with the notch on the eprom. **MAKE SURE THE CHIP IS PLACED ALL THE WAY TO THE BOTTOM OF U78** socket. Placing it at the top of the socket will DESTROY the RAM CLEAR CHIP. You will have extra socket holes at the top of socket if it is located correctly.
3. Locate SW1 dip switch and **turn ON switches 7 & 8** to RAM CLEAR the board.
4. Reseat the MPU board in the slot and make sure it is plugged in all the way
5. **Power on the slot** and allow it to boot and RAM CLEAR. You will have wait a few minutes for the slot to boot. EVO Hybrids boot slowly so be patient.
6. Upon successful booting you will see screen that shows EEPROM options. You must set these correctly for the TITO to work and also so the machine add credits when the service button is pushed.
7. Screen settings are changed by pushing the lite button on the wager deck. Scroll through each setting and select the correct setting by activating the reset key. **ONCE YOU SELECT A SETTING AND TURN THE RESET KEY IT CANNOT BE REVERSED WITHOUT DOING A RAM CLEAR AGAIN.** Make your selections right the first time and double check that they are correct before you turn the reset key. The settings given are for a slot without a hopper or coin comparator. Also your bill validator and printer may be different.
  - a. Current Jurisdiction.....FIVE
  - b. PRIMARY HOST.....SAS HOST
  - c. SECONDARY HOST.....NONE
  - d. SAS VERSION.....5.01
  - e. CHASSIS TYPE.....UPRIGHT
  - f. COIN ACCEPTOR.....NONE
  - g. BILL ACCEPTOR.....JCM WBA
  - h. PRINTER TYPE.....ITHACA 800 PRINTER
  - i. HOPPER TYPE.....NONE
  - j. DOOR TYPE.....PULSE OPTIC
  - k. DOUBLE DOWN.....ON
  - l. TOURNAMENT.....OFF
  - m. EFT.....ENABLE
  - n. RESIDUAL CREDIT MODE....NO GAMBLE AND NO ATTEN. PAY
  - o. WIN EVALUATION.....LEGACY
  - p. CABINET CONFIG.....HYBRID
8. Make sure settings are correct and TURN THE RESET KEY to enable the settings. You will be asked to shut slot off and remove RAM CLEAR chip and reset switches 7 and 8 to off on DIP SW1.
9. Reinsert MPU board in holder and turn slot on and allow it to boot once more. ANOTHER SHORT WAIT

(NEXT PAGE)

10. After a SAM RAM CLEAR and reboot slot automatically goes into a screen calibration mode. Follow directions on the screen to calibrate it.
11. You will now set the currency format, maximum wager, denomination, bill acceptor, maximum/minimum wager. Follow instructions in Bally Module 2 to set these up. Once these are setup your slot will go into DEMO mode.
12. You must set the HOST configuration to leave DEMO mode. To get to Configuration screens open the slot door and turn the reset key once. The slot menu should come up for viewing.
13. Find the HOST configuration button and press it. A HOST settings menu should come up on the screen. You go through this screen similar to EEPROM screen except choices and movements are done directly on screen by touching appropriate button
14. Set and save the HOST configuration as follows. Follow the Bally Module 2 manual to get correct settings:
  - a. TERMINAL ID NUMBER.....001.....(This can be any 3 digit number)
  - b. SERIAL NUMBER.....123456.....(This can be any 6 digit number)
  - c. HOST MODE.....ENABLED
  - d. HOST TYPE.....VALIDATION SYSTEM
  - e. HOST BONUSES.....ENABLE
  - f. PROGRESSIVES.....DISABLE
  - g. VALIDATION TYPE.....SYSTEM
  - h. REMOTE HANDPAY.....DISABLE
  - i. PRINT HANDPAY.....DISABLE
  - j. HANDPAY EXCEPTION.....UNSECURE
  - k. COMM LOSS TILT.....DISABLE
  - l. JRCM CONTROL.....SAS
15. You will also want to set TIME AND DATE and HOPPER/CREDIT LIMITS (I set these limits to Jackpot Payout).
16. Close the slot door and your ready to go. You should be able to print tickets\*\* and reinsert them to add credits. You also should be able to add 1000 credits to your slot by pressing the service button

**\*\*NOTE:** If you go to CASINO LOCATION on the configuration menus you can setup your printed tickets with any custom title LEGEND.